

DCS C-101CC



TACAN/DME CHANNELS AND PAIRED FREQUENCIES

STATION FREQ. MHz	TACAN CHANNEL	INT. FREQ. MHz	REPLY FREQ. MHz	STATION FREQ. MHz	TACAN CHANNEL	INT. FREQ. MHz	REPLY FREQ. MHz
134.40	1X	1025	962	108.55	22Y	1046	1109
134.45	1Y	1025	1088	108.60	23X	1047	984
134.50	2X	1026	963	108.65	23Y	1047	1110
134.55	2Y	1026	1089	108.70	24X	1048	985
134.60	3X	1027	964	108.75	24Y	1048	1111
134.65	3Y	1027	1090	108.80	25X	1049	986
134.70	4X	1028	965	108.85	25Y	1049	1112
134.75	4Y	1028	1091	108.90	26X	1050	987
134.80	5X	1029	966	108.95	26Y	1050	1113
134.85	5Y	1029	1092	109.00	27X	1051	988
134.90	6X	1030	967	109.05	27Y	1051	1114
134.95	6Y	1030	1093	109.10	28X	1052	989
135.00	7X	1031	968	109.15	28Y	1052	1115
135.05	7Y	1031	1094	109.20	29X	1053	990
135.10	8X	1032	969	109.25	29Y	1053	1116
135.15	8Y	1032	1095	109.30	30X	1054	991
135.20	9X	1033	970	109.35	30Y	1054	1117
135.25	9Y	1033	1096	109.40	31X	1055	992
135.30	10X	1034	971	109.45	31Y	1055	1118
135.35	10Y	1034	1097	109.50	32X	1056	993
135.40	11X	1035	972	109.55	32Y	1056	1119
135.45	11Y	1035	1098	109.60	33X	1057	994
135.50	12X	1036	973	109.65	33Y	1057	1120
135.55	12Y	1036	1099	109.70	34X	1058	995
135.60	13X	1037	974	109.75	34Y	1058	1121
135.65	13Y	1037	1100	109.80	35X	1059	996
135.70	14X	1038	975	109.85	35Y	1059	1122
135.75	14Y	1038	1101	109.90	36X	1060	997
135.80	15X	1039	976	109.95	36Y	1060	1123
135.85	15Y	1039	1102	110.00	37X	1061	998
135.90	16X	1040	977	110.05	37Y	1061	1124
135.95	16Y	1040	1103	110.10	38X	1062	999
108.00	17X	1041	978	110.15	38Y	1062	1125
108.05	17Y	1041	1104	110.20	39X	1063	1000
108.10	18X	1042	979	110.25	39Y	1063	1126
108.15	18Y	1042	1105	110.30	40X	1064	1001
108.20	19X	1043	980	110.35	40Y	1064	1127
108.25	19Y	1043	1106	110.40	41X	1065	1002
108.30	20X	1044	981	110.45	41Y	1065	1128
108.35	20Y	1044	1107	110.50	42X	1066	1003
108.40	21X	1045	982	110.55	42Y	1066	1129
108.45	21Y	1045	1108	110.60	43X	1067	1004
108.50	22X	1046	983	110.65	43Y	1067	1130

DCS C-101CC



STATION FREQ. MHz	TACAN CHANNEL	INT. FREQ. MHz	REPLY FREQ. MHz	STATION FREQ. MHz	TACAN CHANNEL	INT. FREQ. MHz	REPLY FREQ. MHz
110.70	44X	1068	1005	134.00	67X	1091	1154
110.75	44Y	1068	1131	134.05	67Y	1091	1028
110.80	45X	1069	1006	134.10	68X	1092	1155
110.85	45Y	1069	1132	134.15	68Y	1092	1029
110.90	46X	1070	1007	134.20	69X	1093	1156
110.95	46Y	1070	1133	134.25	69Y	1093	1030
111.00	47X	1071	1008	112.30	70X	1094	1157
111.05	47Y	1071	1134	112.35	70Y	1094	1031
111.10	48X	1072	1009	112.40	71X	1095	1158
111.15	48Y	1072	1135	112.45	71Y	1095	1032
111.20	49X	1073	1010	112.50	72X	1096	1159
111.25	49Y	1073	1136	112.55	72Y	1096	1033
111.30	50X	1074	1011	112.60	73X	1097	1160
111.35	50Y	1074	1137	112.65	73Y	1097	1034
111.40	51X	1075	1012	112.70	74X	1098	1161
111.45	51Y	1075	1138	112.75	74Y	1098	1035
111.50	52X	1076	1013	112.80	75X	1099	1162
111.55	52Y	1076	1139	112.85	75Y	1099	1036
111.60	53X	1077	1014	112.90	76X	1100	1163
111.65	53Y	1077	1140	112.95	76Y	1100	1037
111.70	54X	1078	1015	113.00	77X	1101	1164
111.75	54Y	1078	1141	113.05	77Y	1101	1038
111.80	55X	1079	1016	113.10	78X	1102	1165
111.85	55Y	1079	1142	113.15	78Y	1102	1039
111.90	56X	1080	1017	113.20	79X	1103	1166
111.95	56Y	1080	1143	113.25	79Y	1103	1040
112.00	57X	1081	1018	113.30	80X	1104	1167
112.05	57Y	1081	1144	113.35	80Y	1104	1041
112.10	58X	1082	1019	113.40	81X	1105	1168
112.15	58Y	1082	1145	113.45	81Y	1105	1042
112.20	59X	1083	1020	113.50	82X	1106	1169
112.25	59Y	1083	1146	113.55	82Y	1106	1043
133.30	60X	1084	1021	113.60	83X	1107	1170
133.35	60Y	1084	1147	113.65	83Y	1107	1044
133.40	61X	1085	1022	113.70	84X	1108	1171
133.45	61Y	1085	1148	113.75	84Y	1108	1045
133.50	62X	1086	1023	113.80	85X	1109	1172
133.55	62Y	1086	1149	113.85	85Y	1109	1046
133.60	63X	1087	1024	113.90	86X	1110	1173
133.65	63Y	1087	1150	113.95	86Y	1110	1047
133.70	64X	1088	1151	114.00	87X	1111	1174
133.75	64Y	1088	1025	114.05	87Y	1111	1048
133.80	65X	1089	1152	114.10	88X	1112	1175
133.85	65Y	1089	1026	114.15	88Y	1112	1049
133.90	66X	1090	1153	114.20	89X	1113	1176
133.95	66Y	1090	1027	114.25	89Y	1113	1050

DCS C-101CC



STATION FREQ. MHz	TACAN CHANNEL	INT. FREQ. MHz	REPLY FREQ. MHz	STATION FREQ. MHz	TACAN CHANNEL	INT. FREQ. MHz	REPLY FREQ. MHz
114.30	90X	1114	1177	116.15	108Y	1132	1069
114.35	90Y	1114	1051	116.20	109X	1133	1196
114.40	91X	1115	1178	116.25	109Y	1133	1070
114.45	91Y	1115	1052	116.30	110X	1134	1197
114.50	92X	1116	1179	116.35	110Y	1134	1071
114.55	92Y	1116	1053	116.40	111X	1135	1198
114.60	93X	1117	1180	116.45	111Y	1135	1072
114.65	93Y	1117	1054	116.50	112X	1136	1199
114.70	94X	1118	1181	116.55	112Y	1136	1073
114.75	94Y	1118	1055	116.60	113X	1137	1200
114.80	95X	1119	1182	116.65	113Y	1137	1074
114.85	95Y	1119	1056	116.70	114X	1138	1201
114.90	96X	1120	1183	116.75	114Y	1138	1075
114.95	96Y	1120	1057	116.80	115X	1139	1202
115.00	97X	1121	1184	116.85	115Y	1139	1076
115.05	97Y	1121	1058	116.90	116X	1140	1203
115.10	98X	1122	1185	116.95	116Y	1140	1077
115.15	98Y	1122	1059	117.00	117X	1141	1204
115.20	99X	1123	1186	117.05	117Y	1141	1078
115.25	99Y	1123	1060	117.10	118X	1142	1205
115.30	100X	1124	1187	117.15	118Y	1142	1079
115.35	100Y	1124	1061	117.20	119X	1143	1206
115.40	101X	1125	1188	117.25	119Y	1143	1080
115.45	101Y	1125	1062	117.30	120X	1144	1207
115.50	102X	1126	1189	117.35	120Y	1144	1081
115.55	102Y	1126	1063	117.40	121X	1145	1208
115.60	103X	1127	1190	117.45	121Y	1145	1082
115.65	103Y	1127	1064	117.50	122X	1146	1209
115.70	104X	1128	1191	117.55	122Y	1146	1083
115.75	104Y	1128	1065	117.60	123X	1147	1210
115.80	105X	1129	1192	117.65	123Y	1147	1084
115.85	105Y	1129	1066	117.70	124X	1148	1211
115.90	106X	1130	1193	117.75	124Y	1148	1085
115.95	106Y	1130	1067	117.80	125X	1149	1212
116.00	107X	1131	1194	117.85	125Y	1149	1086
116.05	107Y	1131	1068	117.90	126X	1150	1213
116.10	108X	1132	1195	117.95	126Y	1150	1087